

Remote Indicating Lamp



Feature

This unit is designed to ensure that alarm signal can be actually transmitted to all locations in order to prevent any missing signal caused by separated zones. Especially for the closed room, any fire condition happened can be transmitted to outside for pre-fire alarm notification.

Construction and Characteristics

- Enlarged indicating lamp.(AH-91213)
- Build-in FLASH light, higher lumination and longer operating life. (AH-91213)
- Parallel type wiring.
- Low current consumption, so with 24VDC/2A control panel it can connect with up to 10 of AH-91213 or 100 of AH-01313.
- Individual revert switch.(AH-91213)

Specification

Model	AH-91213	AH-01313
Power Source	24VDC	24VDC
Standby Current	24VDC 12mA	N/A
Operating Current	160mA	12mA
Ambient Temperature	-10 °C ~ +55 °C	
Relative Humidity	10 ~ 95%	
Material	Fire-proof plastic	
Dimensions	120mm (H) x 120mm (W) x 42mm (D)	70mm (H) x 70mm (W) x 15mm (D)
Weight	About 140g	About 32g
Color	White surface / Red lamp cover	White surface / Red LED

Wiring Diagram

Fire Alarm Control Panel

Remote Indicating Lamp

